


DUOX plus  
by FERMAX

More powerful



THE ONLY **FULLY DIGITAL**  
DOOR ENTRY SYSTEM **IN 2 WIRES**



# DUOX<sup>plus</sup>

More powerful

**FERMAX**



## The new advanced DUOX system offers much more

Higher performance and increased capacity, faster and more user-friendly, but above all, it brings us to a new technological dimension destined to define the future of video door systems.

**DUOX PLUS** brings the **MOST POWERFUL**  
2-wire digital system to your home.



## 2 wires

A fully digital door entry system that works with 2 non-polarised wires from start to finish in the installation.

## scalable

Up to 10 panels and 10 guard units at the general entrances.

Up to 10 panels and 10 guard units in each building or block of apartments.

Up to 100 blocks and sub-blocks.

## user-friendly

Since the system is entirely digital, the type of wiring has much less of an effect on the quality and performance of the system.

Furthermore, very few intermediary elements are required, which saves considerable time in the installation.

## intuitive

The DUOX PLUS monitors can be programmed in just a few seconds, directly from the OSD menu.

## no limits

DUOX is designed to work with all kinds of projects; large or small, simple or complex, vertical structures or horizontal installations.

## product range

A broad variety of outdoor panels and indoor terminals with an exclusive design and advanced functions, without any increase in price.

## connectivity for everyone

With DUOX PLUS, Fermax can introduce any kind of building or home to the world of connectivity, incorporating mobile call divert into even the most basic monitors.

# + capacity

- LONGER DISTANCES
- INCREASED VOLTAGE, LESS CONSUMPTION
- GREATER NUMBER OF TERMINALS PER POWER SUPPLY

DUOX PLUS allows you to push the boundaries of digital technology. Thanks to the digitalisation of the system, it can now be used in all kinds of installations.

The more complex the installation is, the more powerful DUOX PLUS will be.



# + flexibility

- MORE APARTMENTS PER FLOOR
- BETTER SERVICE WITH ANY CABLE
- SIMPLER INSTALLATION

Can be easily replaced, with no need to change the installed wiring. Considerable time saving during installation and maintenance.






# + technology

- MORE DIGITISED
- 2 SIMULTANEOUS AUDIO/VIDEO COMMUNICATION CHANNELS IN THE SAME RISER
- MORE RESOLUTION AND FLUIDITY ON VIDEO QUALITY
- AUDIO QUALITY ENTIRELY FREE OF INTERFERENCE

- Designed to handle external interference.
- Consistent quality throughout the installation.
- The regenerators boost the signal.
- Capable of communicating over long distances.



# + functions

- ONE SINGLE CONNECTOR FOR ALL THE MONITORS
- NEW VEO TELEPHONE
- BETTER VISUAL ANGLE ON THE OUTDOOR PANEL

DUOX PLUS is a system designed for everyone. Not just for its intuitive and attractive design, but also because it provides more advantages and functions for both the installer and the end user, at no additional cost.








# connectivity



- ALL VIDEO KITS COME WITH A WiFi MONITOR AS STANDARD
- INCREASED SECURITY
- FASTER COMMUNICATION



Our systems provide a wide range of different possibilities for security, mobility and comfort, inside and outside the home.

**All video kits now include a WiFi monitor as standard, at no extra cost!**



DUOXplus

CONNECTIVITY FOR ALL






# DUOX plus

FERMAX



product range






# WiFi monitors

## Features of WiFi monitors

VEO and VEO-XS 4.3" colour monitors and VEO-XL 7" colour monitors, made from high-impact ABS plastic and UV protection, with settings for contrast, brightness, colour, audio volume, call ring tone volume, do not disturb function, doorbell, date and time, silicone buttons for activating the lock release that are pleasant to the touch, access to the main OSD menu from the screen, activation of the outdoor panel camera, and various other additional configurable functions such as activating second access, courtesy light, etc. Available in white and for surface installation.

Three WiFi monitor options: the VEO monitor with its unique handset design incorporating a magnet that enables the user to hang up correctly at the end of the conversation, and the VEO-XS and VEO-XL hands-free monitors.

NEW



## Photocaller



Automatically captures an image of the person who calls. If the user decides to activate this function, the monitor will save up to 150 images, with the date and time when they were taken. Once maximum capacity has been reached, taking a new photo will delete the first one that was saved. The screen will always tell you if there are photos that you haven't seen or if the date/time has not been configured.

## Call divert to mobile

The DUOX PLUS VEO, VEO-XS and VEO-XL WiFi monitors are equipped with a WiFi connection, allowing for calls to be diverted to mobile devices.


With the BLUE app by FERMAX you can manage all the video door functions and much more directly from your mobile phone or tablet.






Free App








## VEO, VEO-XS AND VEO-XL WiFi MONITORS

- 9446** DUOX PLUS VEO WiFi MONITOR
-  **9456** DUOX PLUS VEO WiFi MONITOR WITH INDUCTIVE LOOP  
Dimensions: 200x200x23 mm (44 mm with handset).
- 9449** DUOX PLUS VEO-XS WiFi MONITOR
-  **9459** DUOX PLUS VEO-XS WiFi MONITOR WITH INDUCTIVE LOOP  
Hands-free. Dimensions: 125x165x21mm.
- 9469** DUOX PLUS VEO-XL WiFi MONITOR
-  **9479** DUOX PLUS VEO-XL WiFi MONITOR WITH INDUCTIVE LOOP  
Hands-free. Dimensions: 185x185x21mm.
- 9447** DUOX PLUS CONNECTOR  
Mounting support for VEO, VEO-XS and VEO-XL monitors.




<< If you'd like to watch our video to find out more, scan this code






# monitors and telephones


## VEO, VEO-XS AND VEO-XL MONITORS



**9445** DUOX PLUS VEO MONITOR

 **9455** DUOX PLUS VEO MONITOR WITH INDUCTIVE LOOP


Dimensions: 200x200x23 mm (44 mm with handset).




**9448** DUOX PLUS VEO-XS MONITOR

 **9458** DUOX PLUS VEO-XS MONITOR WITH INDUCTIVE LOOP

Hands-free. Dimensions: 125x165x21 mm.



**9468** DUOX PLUS VEO-XL MONITOR

 **9478** DUOX PLUS VEO-XL MONITOR WITH INDUCTIVE LOOP

Hands-free. Dimensions: 185x185x21 mm.

**9447** DUOX PLUS CONNECTOR Mounting support for VEO, VEO-XS and VEO-XL monitors.

## VEO, LOFT AND iLOFT TELEPHONES



**3444** DUOX PLUS VEO TELEPHONE

Includes volume control.  
Dimensions: 82x214x43 mm.



**3452** DUOX PLUS LOFT EXTRA TELEPHONE

Includes 2 buttons for extra functions: turn on lights, open 2nd door, etc.  
Dimensions: 85x220x40 mm.



**3450** iLOFT DUOX PLUS TELEPHONE

Hands-free. Includes volume control and a button for additional function.  
Dimensions: 90x146.5x20 mm.



## AUDIO GUARD UNIT

**9423** DUOX PLUS AUDIO VEO GUARD UNIT

DUOX PLUS Audio Guard Unit has a multi-functional 4,3" capacitive touchscreen and quick function access buttons for easy convenient management. Its unique handset design incorporating a magnet enables the user to put it back into position correctly. It includes a stainless steel desktop support. It allows a surface installation.

Dimensions: 200x200 mm. Support included.

Dimensions: (width) x (height) x (depth) mm.





# outdoor panels

DUOXplus



## SKYLINE Modular design. Anodised aluminium. IP43 IK07

### FRAMES




### VIDEO AUDIO




### DOUBLE PUSH BUTTONS




### SIMPLE PUSH BUTTONS



### INFORMATION MODULES




### ACCESS CONTROL



### DIGITAL MODULES



### ACCESSORIES



ACCESSORIES	S1 (1V)	S2 (2V)	S4 (3V)	S5 (4V)	S6 (5V)	S7 (6V)	S8 (7V)	S9 (8V)
<b>flush box</b>	ref.8851 115x114x45	ref.8852 115x138x45	ref.8854 115x185x45	ref.8855 115x233x45	ref.8856 115x280x45	ref.8857 115x328x45	ref.8858 115x375x45	ref.8982 115x420.5x45
<b>surface box</b>	ref.7061 130x128x33	ref.7062 130x151x33	ref.7064 130x199x33	ref.7065 130x246x33	ref.7066 130x294x33	ref.7067 130x341x33	ref.7068 130x389x33	ref.7069 130x436.5x33
<b>simple hood</b>	ref.8400 135x130	ref.8401 135x155	ref.8403 135x203	ref.8404 135x250	ref.8405 135x300	ref.8406 135x345	ref.8407 135x393	ref.8480 135x440.5
<b>modular decorative frame*</b>	ref.9191 211x210	ref.9192 211x234	ref.9194 211x281	ref.9195 211x329	ref.9196 211x376	ref.9197 211x424	ref.9198 211x471	ref.9199 211x519
<b>simple city decorative frame</b>	ref.8251 225x310	ref.8252 225x310	ref.8254 225x375	ref.8255 225x375	ref.8256 225x450	ref.8257 225x450	ref.8258 225x450	ref.8259 225x495
<b>angular complement</b>	ref.8378	ref.8379	ref.8381	ref.8382	ref.8383	ref.8384	ref.8385	ref.8386

If the configuration requires more than one panel, they will need to be connected together with a connection cable (ref. 2541) (1 cable for each additional panel) and a set of joining bolts (ref. 8829) to attach them to unite the flush boxes.

\* To make DOUBLE modular frames, add to the SINGLE frame a DOUBLE PANEL MODULAR FRAME KIT (ref. 9200). Horizontal: 341 mm.

\* To make TRIPLE modular frames, add to the SINGLE frame a TRIPLE PANEL MODULAR FRAME KIT (ref. 9201). Horizontal: 471 mm.



# outdoor panels



## CITYLINE Monoblock design panel. Anodised aluminium. IP43 IK07

### DIGITAL CITYLINE

ref.73871      ref.7310      ref.73878

The DIGITAL panels include a keypad and a 3.5" EXTRA display. The keypad has an access control function (10,000 codes).

**73871** DUOX PLUS DIGITAL CITY VIDEO PANEL S7  
**73811** DUOX PLUS DIGITAL CITY VIDEO PANEL PROX S8

**73878** DUOX PLUS DIGITAL 1/W CITY VIDEO PANEL S7  
**73818** DUOX PLUS DIG 1/W CITY VIDEO PANEL PROX S8  
 With a push button to call any concierge  
 DUOX PLUS ref. 9423.

**7310** DIRECTORY PANEL S7  
**8857** FLUSH BOX S7  
**8858** FLUSH BOX S8  
**8829** JOINING BOLTS SET

### DIRECT CITYLINE

ref.73631      ref.7309      ref.73638

The DIRECT panels have a keypad for calling homes. The keypad allows 1 code for opening the door. We recommend adding a DIRECTORY PANEL.

**73631** DUOX PLUS DIRECT CITY VIDEO PANEL S5  
**73638** DUOX PLUS DIRECT 1/W CITY VIDEO PANEL S5  
 With a push button to call any concierge  
 DUOX PLUS ref. 9423.

**7309** DIRECTORY PANEL S5  
**8855** FLUSH BOX S5  
**8829** JOINING BOLTS SET

### PUSH BUTTONS CITYLINE

**SERIES 1 // Panel: 130x128**  
 Flush box (ref.8851): 115x114x45

ref.40708      ref.40008      ref.40704      ref.40004  
 1 PUSH.      2 PUSH.      1 PUSH.      2 PUSH.

**SERIES 2 // Panel: 130x151**  
 Flush box (ref.8852): 115x138x45

ref.40718      ref.40018      ref.40714  
 2 PUSH.      4 PUSH.      2 PUSH.

**SERIES 3 // Panel: 130x175**  
 Flush box (ref.8853): 115x162x45

ref.40728      ref.40724  
 3 PUSH.      3 PUSH.

**SERIES 4 // Panel: 130x199**  
 Flush box (ref.8854): 115x185x45

ref.40748      ref.40744  
 4 PUSH.      4 PUSH.

The CITYLINE outdoor panels with push buttons (except the outdoor panels in size S1, both AUDIO and VIDEO, with 1 and 2 push buttons), always require a call extension module, depending on the number of push buttons (ref. 2008 - 8 call extension module, ref. 2441 - 16 call extension module).

If the configuration requires more than one panel, they will need to be connected together with a connection cable (ref. 2541) (1 cable for each additional panel) and a set of joining bolts (ref. 8829) to attach them to unite the flush boxes.





**MARINE** Stainless steel vandal-proof panel. 316L. IP54 IK09

**SERIE ST1 Panel: 150x180**

Flush box. (ref.4641): 130x160x55



**ref.44438**  
1 Push.  
150x180



**ref.44338**  
1 Push.  
150x180



**ref.44348**  
2 Push.  
150x180



**ref.44358**  
2 Push.  
150x240



**ref.44368**  
3 Push.  
150x240



**ref.44378**  
4 Push.  
150x240

The MARINE outdoor panels with push buttons (except 1 and 2 ways VIDEO panels), always require a call extension module, depending on the number of push buttons. (ref. 2008 - 8 call extension module, ref. 2441 - 16 call extension module).



ref.55261



ref.5471



ref.55268

- 55261** DUOX PLUS DIGITAL MARINE VIDEO PANEL ST3
- 55281** DUOX PLUS DIGITAL MARINE VIDEO PANEL W/PROX ST4
- 55268** DUOX PLUS DIG 1/W MARINE VID PANEL ST3+
- 55288** DUOX PLUS DIG 1/W MARINE VID PANEL PROX ST4  
With a push button to call any concierge  
DUOX PLUS ref. 9423.
- 5471** DIRECTORY PANEL ST3  
Dimensions: 150x360mm

ACCESSORIES	FLUSH BOX	SURFACE BOX (with hood)	SIMPLE HOOD
ST1	<b>ref.4641</b> 130x160x55	<b>ref.4645</b> 154x184x96	<b>ref.4701</b>
ST2	<b>ref.4642</b> 130x220x55	<b>ref.4646</b> 154x244x96	<b>ref.4702</b>
ST3	<b>ref.4643</b> 130x340x55	<b>ref.4647</b> 154x364x96	<b>ref.4703</b>
ST3+	<b>ref.4653</b> 130x400x55	<b>ref.4654</b> 154x423x96	<b>ref.4655</b>
ST4	<b>ref.4644</b> 130x465x55	<b>ref.4648</b> 154x489x96	<b>ref.4704</b>

If the configuration requires more than one panel, they will need to be connected together with a connection cable (ref. 2541) (1 cable for each additional panel) and a set of joining bolts (ref. 2289) to attach them to unite the flush boxes.

Dimensions: (width) x (height) x (depth) mm.



# outdoor panels

## MARINE ELITE



RAL 9005



FERMAX has a laser-cut machining line for stainless steel panels. This process allows us to offer complete flexibility when it comes to producing the required Marine panel, with optimal delivery time for personalisation.

RAL 3020



RAL 5005



RAL 9018



RAL 9016



Check for availability of other colours.

The MARINE Elite panels are available in several colours: indicate the desired RAL when ordering your panel.



### MARINE SPECIAL (made to measure)

- 3172** MARINE SPECIAL PANEL
- 4579** MARINE SPECIAL PANEL HOOD
- 4580** MARINE SPECIAL PANEL FLUSH BOX
- 4581** MARINE SPECIAL PANEL SURFACE BOX WITH HOOD





## DECODER



**9419** DUOX PLUS  
DECODER/ISOLATOR

10-outputs floor decoder. One output per home, allowing a maximum of one terminal (monitor/telephone) per home. Multiple decoders can be installed on each floor.

Each output regenerates the bus signal, so it acts as a regenerator and allows to increase the diversion distances on a floor up to 100 m.

In the event of a malfunction (short circuit) of any of the decoder's outputs, both the input DUOX PLUS bus and the rest of the outputs will continue to operate normally.

It is not necessary to enter a house to program the address of the terminals since the decoder includes a group of microswitches (dipswitches) to program the addresses of each of its outputs.

The decoder is powered directly from the DUOX PLUS bus. With mounting on DIN10 rail.

## POWER SUPPLY AND ADAPTORS



**3255** DUOX PLUS LINE ADAPTOR  
Necessary at the beginning and the end of every riser.



**4825** POWER SUPPLY + FILTER  
24Vdc-2.5A DIN10



**4840** POWER SUPPLY DIN-6  
100-240Vac/24Vdc-2A

To be used exclusively with the filter ref. 3289 or with the 2 WAY Regenerator ref. 3269.



**3289** FILTER DUOX PLUS 24Vdc

To be used with the PSU ref. 4840, in those installations where the PSU ref. 4825 cannot be used due to its dimensions. Cannot be used with 18Vdc power supplies, which must be installed with filter ref. 3244.



**4802** POWER SUPPLY 12Vac/1A DIN4

**4800** POWER SUPPLY 12Vac/1,5A DIN4

For altern lock release.

Terminal consumption table per power supply in **DISTRIBUTION** (4 x floor)

	VEO/VEO XS no WiFi	VEO/VEO XS WiFi	VEO XL no WiFi	VEO XL WiFi	Telephones
1,0 mm <sup>2</sup>	40	28	34	24	80
0,5 mm <sup>2</sup>	40	24	30	18	80
0,2 mm <sup>2</sup>	36	20	24	12	72

Terminal consumption table per power supply in **CASCADE**


	VEO/VEO XS no WiFi	VEO/VEO XS WiFi	VEO XL no WiFi	VEO XL WiFi	Telephones
1,0 mm <sup>2</sup>	40	26	30	20	60
0,5 mm <sup>2</sup>	32	20	22	14	45
0,2 mm <sup>2</sup>	18	12	12	10	25





## REGENERATORS

They allow the signal to be regenerated and amplified in both ways, and they also increase distances and the number of terminals. The sections connected to the input and output protect against short-circuit, overloads and signal reflections. Maximum of 5 units in cascade. Up to 99 if they are connected in parallel.



**3269** 2/W DUOX PLUS REGENERATOR

It has 1 input and 2 outputs. By having 2 outputs (also isolated from each other) it enables the number of risers to be increased. Requires 24Vdc power supply without filter (ref. 4840).

For more information: [www.fermax.com/intl/en/pro/documents](http://www.fermax.com/intl/en/pro/documents)



**3268** 1/W DUOX PLUS DUAL REGENERATOR

It has 1 input and 1 output. As per factory default settings, electrical energy does not flow, but this can be configured via a dipswitch so that the data (which regenerates) as well as the power supply can pass through. That way there is no need to always install a power supply at the output. The number of devices that can be fed at the output without an additional power supply units will depend on the power that reaches the regenerator.

For more information: [www.fermax.com/intl/en/pro/documents](http://www.fermax.com/intl/en/pro/documents)

	No. of inputs	No. of outputs	Regenerates	Isolates	Incorporates power supply filter	Additional conversation channel per riser
<b>3269</b>	1	2	YES	YES	YES	NO
<b>3268</b>	1	1	YES	YES	NO	YES (in multichannel mode)

## ACCESORIOS



**3233** DUOX PLUS BASIC RELAY

Basic functions. Allows you to activate an additional function from F1 or F2 of the DUOX PLUS terminals, without additional wiring. The relay can also be activated by the call or by activating the lock release. It can be connected at any point of the bus.



**3267** DUOX PLUS RELAY MODULE

Advanced functions. Allows you to pair 2 relays, 1 as a transmitter and other as a receiver, to perform remote activations. An address can be programmed with the address assistance (001-999) using the DUOX PLUS Programmer ref. 3254 via the relay's telephone connector.



**9444** DUOX PLUS CAMERA INTERFACE

The DUOX PLUS camera interface is a device that allows you to integrate CCTV analog composite video cameras in a DUOX PLUS installation. An interface is required for each camera installed in a DUOX PLUS installation (up to 2 per block and 1 general entrance).



**9443** DUOX PLUS LIFT CONTROL UNIT

It is used to provide a lift control service for the DUOX PLUS installation. This allows visitors to access only the floor corresponding to the flat that has opened the door for them. It is an interface between DUOX PLUS and MDS. The MDS Central Unit is responsible for the lift control function, as well as the MDS relay decoders.



- 67501** UNIVERSAL LOCK RELEASE 990N-P22 MAX 10-24Vac/dc
- 6750** UNIVERSAL MECHANISM 990N MAX 10-24Vac/dc
- 6752** UNIVERSAL MECHANISM 990A MAX 12-24Vac/dc

- 2040** CALL EXTENSION MODULE
- 2438** LIGHT/DOOR BELL ACTIVATOR

## VIDEO DOOR KITS

WIFI  
MONITOR  
AS STANDARD





**94411** 1/W DUOX PLUS VEO WiFi KIT  
**94421** 2/W DUOX PLUS VEO WiFi KIT



**94511** 1/W DUOX PLUS VEO-XS WiFi KIT  
**94521** 2/W DUOX PLUS VEO-XS WiFi KIT



**9471** 1/W DUOX PLUS VEO-XL WiFi KIT  
**9472** 2/W DUOX PLUS VEO-XL WiFi KIT



**49081** 1/W DUOX PLUS VEO WiFi ONE-TO-ONE KIT




**50731** 1/W DUOX PLUS VEO-XS WiFi MARINE KIT



**50831** 1/W DUOX PLUS VEO-XS WiFi MARINE BLACK KIT



**50781** 1/W DUOX PLUS MARINE ONE-TO-ONE VEO-XS WiFi KIT



**49071** 1/W DUOX PLUS VEO WiFi MEMOVISION KIT




**49121** 1/W DUOX PLUS VEO-XS WiFi MEMOVISION KIT

### KITS EXTENSIONS

**INDOOR:** up to 2 terminals without additional power supply (total terminals per home = 3). Depending on the type of cable and distances, additional power supply (ref. 4825), line adaptors ref. 3255 and/or regenerators might be required.

**OUTDOOR:** It is possible to extend the installation by adding more outdoor panels (up to 10). Depending on the type of cable and topology, additional power supply (ref. 4825), line adaptors ref. 3255 and/or regenerators might be required.


### INSTALLATION DIAGRAM




## AUDIO KITS



**49201** 1/W DUOX PLUS AUDIO CITY VEO KIT  
**49211** 2/W DUOX PLUS AUDIO CITY VEO KIT



**49131** 1/W DUOX PLUS AUDIO MEMOPHONE CITY VEO KIT



**50771** 1/W DUOX PLUS AUDIO CITY iLOFT KIT




**50761** 1/W DUOX PLUS AUDIO MARINE iLOFT KIT

### KITS EXTENSIONS

**INDOOR:** up to 2 terminals without additional power supply (total terminals per home = 3). Depending on the type of cable and distances, additional power supply (ref. 4825), line adaptors ref. 3255 and/or regenerators might be required.

**OUTDOOR:** It is possible to extend the installation by adding more outdoor panels (up to 10). Depending on the type of cable and topology, additional power supply (ref. 4825), line adaptors ref. 3255 and/or regenerators might be required.

### INSTALLATION DIAGRAM



### ACCESSORIES

#### VEO, VEO-XS AND VEO-XL MONITORS

- 3388** UNIVERSAL DECORATIVE FRAME 120X240 (ONLY VEO-XS)
- 3389** UNIVERSAL LARGE DECORATIVE FRAME 210X240
- 9410** VEO MONITOR DESKTOP SUPPORT
- 9420** VEO-XS AND VEO-XL MONITOR DESKTOP SUPPORT

#### iLOFT TELEPHONE

- 3388** UNIVERSAL DECORATIVE FRAME 120X240
- 3389** UNIVERSAL LARGE DECORATIVE FRAME 210X240
- 5636** iLOFT TELEPHONE DESKTOP SUPPORT

#### VEO AND LOFT TELEPHONES

- 3380** LOFT TELEPHONE DECORATIVE FRAME 120X240 200X240
- 3388** UNIVERSAL DECORATIVE FRAME 120X240
- 3389** UNIVERSAL LARGE DECORATIVE FRAME 210X240
- 3749** VEO / LOFT TELEPHONE DESKTOP SUPPORT
-  **3441** LOFT HANDSET WITH INDUCTIVE LOOP
-  **3443** VEO HANDSET WITH INDUCTIVE LOOP

#### CITYLINE AND MARINE PANELS

SEE OUTDOOR PANEL SECTION



# DUOX<sup>plus</sup>


FERMAX

technical information



**DIAGRAM. DUOX PLUS VIDEO**

1 ACCESS VIDEO DUOX PLUS TO 2 RISERS OF 4 FLOORS. 2 APARTMENTS PER FLOOR









# CONTACTS

FERMAX ELECTRÓNICA, S.A.U.  
Avda. Tres Cruces, 133 • 46017 VALENCIA (Spain)

[www.fermax.com](http://www.fermax.com)

## TELEPHONE


+34 96 317 80 11

[export@fermax.com](mailto:export@fermax.com)

### SALES ASSISTANCE

 +34 963 178 011

### AFTER SALES ASSISTANCE

 +34 963 178 002

## SUBSIDIARIES AND REPRESENTATIVE OFFICES

### FERMAX ASIA PACIFIC PTE LTD

Block 13, Lorong 8 Toa Payoh #07-12 Braddell Tech  
319261 Singapore  
 +65 6259 0700  
[fermax@fermax.com.sg](mailto:fermax@fermax.com.sg) / [www.fermax.com.sg](http://www.fermax.com.sg)

### FERMAX BELGIUM

Nieuwstraat,10 • 1570 Galmaarden • Belgium  
 +32 54 31 82 80  
[info@fermax.be](mailto:info@fermax.be) / [www.fermax.be](http://www.fermax.be)

### FERMAX COLOMBIA

Cll 93B No 19-35/57 Oficina 201 • Bogotá D.C.- Colombia  
 +57 1 6915832  
[fermax@fermax.com.co](mailto:fermax@fermax.com.co) / [www.fermax.com.co](http://www.fermax.com.co)

### FERMAX FRANCE S.A.S.U.

13 Rue de la perdrix • Bâtiment 9 Hall B. ZI Paris Nord 2  
93290 Tremblay en France  
 +33 1 43 60 11 20  
[fermax@fermax.fr](mailto:fermax@fermax.fr) / [www.fermax.fr](http://www.fermax.fr)

### FERMAX MIDDLE EAST REGIONAL OFFICE

Office No. 7WA 3046  
P.O. Box 293824  
Dubai airport Freezone - Dubai (UAE)  
 +971 4 253 3369 - FAX: +971 4 253 3370  
[mideast@fermax.com](mailto:mideast@fermax.com) / [www.fermax.com](http://www.fermax.com)


### FERMAX PORTUGAL

Via do Oriente nº12 E, Parque das Nações Norte  
1990-514 LISBOA  
 +351 915169236  
[portugal@fermax.pt](mailto:portugal@fermax.pt) / [www.fermax.pt](http://www.fermax.pt)

### FERMAX POLSKA Sp. z o.o

ul. Szkolna 86 • 62-002 Suchy Las  
 +48 618 112 303 - FAX +48 618 112 343  
[fermax@fermax.pl](mailto:fermax@fermax.pl) / [www.fermax.pl](http://www.fermax.pl)

### Office in Warsaw

ul. Minska 63a lok. 47 (budynek Pryzmat)  
03-828 Warszawa  
 +48 22 3308150

### FERMAX (SHANGHAI) ELECTRONICS CO. LTD.

Room 705, Building A, Hongwell Lotus Plaza,  
No. 1308, Lianhua Road • Shanghai  
 +86 21-64659292 - FAX: +86 21-64654992  
[fermax@fermax.com.cn](mailto:fermax@fermax.com.cn) / [www.fermax.com.cn](http://www.fermax.com.cn)

### FERMAX TURKEY

Perpa Ticaret Merkezi A • Blok Kat:11 No:1567  
Sisli / Istanbul  
 +90 212 3560565 - FAX +90 212 3560691  
[info@fermax.com.tr](mailto:info@fermax.com.tr) / [www.fermax.com.tr](http://www.fermax.com.tr)

### FERMAX UK LTD

36 Saffron Court  
Southfields Industrial Estate  
Laindon, Essex, SS15 6SS  
 +44 01277 634555  
[fermax@fermaxuk.com](mailto:fermax@fermaxuk.com) / [www.fermax.co.uk.com](http://www.fermax.co.uk.com)

### SECURE ENGINEERING Ltd

Advanced Technology Centre  
East Sutton, Maidstone, Kent. ME17 3DD  
 +44 01622 844 244  
[info@secureeng.co.uk](mailto:info@secureeng.co.uk) / [www.secureeng.co.uk](http://www.secureeng.co.uk)

**DUOX PLUS CATALOGUE**  
2nd Edition. January 2021

**DESIGN AND LAYOUT**  
FERMAX ELECTRÓNICA, S.A.U

**FERMAX**

CONNECTIVITY FOR ALL

[www.fermax.com](http://www.fermax.com) | [fermax@fermax.com](mailto:fermax@fermax.com)

